


# **CO-D4 Carbon Monoxide Sensor** Miniature Size



Figure 1 CO-D4 Schematic Diagram

PATENTED and PATENT PENDING



	(A three pin version is available on request, coded CO-DF)		
PERFORMANCE	Sensitivity Response time Zero current Resolution Range Linearity Overgas limit	nA/ppm in 400ppm CO t <sub>90</sub> (s) from zero to 400ppm CO % 22°C ppm equivalent in zero air RMS noise (ppm equivalent) ppm limit of performance warranty ppm CO error at full scale, linear at zero and 400ppm of maximum ppm for stable response to gas pulse	30 to 55 < 25 < ± 3 < 1.5 1,000 CO ± 40 2,000
LIFETIME	Zero drift Sensitivity drift Operating life	ppm equivalent change/year in lab air % change/year in lab air, monthly test months until 80% original signal (24 month warranted)	< 0.5 < 6 > 24
ENVIRONMENTAL	Sensitivity @ -20°C Sensitivity @ 50°C Zero @ -20°C Zero @ 50°C	% (output @ -20°C/output @ 20°C) @ 400ppm CO % (output @ 50°C/output @ 20°C) @ 400ppm CO ppm equivalent change from 20°C ppm equivalent change from 20°C	45 to 70 105 to 125 < ± 2 < ± 4
CROSS SENSITIVITY	Filter capacity H <sub>2</sub> S sensitivity NO <sub>2</sub> sensitivity Cl <sub>2</sub> sensitivity NO sensitivity SO <sub>2</sub> sensitivity H <sub>2</sub> sensitivity C <sub>2</sub> H <sub>4</sub> sensitivity NH <sub>3</sub> sensitivity	ppm-hrs	20,000 < 0.1 < 0.1 < 0.1 < 50 < 0.1 < 70 < 100 < 0.1
KEY SPECIFICATIONS	Temperature range Pressure range Humidity range Storage period Load resistor Weight	$^{\mathrm{O}}\mathrm{C}$ kPa %rh (see note below) months @ 3 to $20^{\mathrm{O}}\mathrm{C}$ (stored in sealed pot) $\Omega$ (recommended) g	-20 to 50 80 to 120 15 to 90 6 10 to 47 < 2

Note: Above 85% rh and 40°C a maximum continuous exposure period of 10 days is warranted. Where such exposure occurs the sensor will recover normal electrolyte volumes when allowed to rest at lower %rh and temperature levels for several days.



At the end of the product's life, do not dispose of any electronic sensor, component or instrument in the domestic waste, but contact the instrument manufacturer, Alphasense or its distributor for disposal instructions.

### Apollosense Ltd

Adress: Room 712, Huaneng Building, Shennan Zhong Road, Shenzhen 518031,

Tel: (86-755) 83680810 83680820 83680830 83680860 Fax: (86-755) 83680866

Adress: Unit 1502, Hollywood Plaza, 610 Nathan Road, Mong Kok, Kln., H.K.

Tel: (852) 2737 0903 Fax: (852) 2737 0938 Email: sales@apollounion.com



pecification

chnical

## **CO-D4 Performance Data**

#### Figure 2 Sensitivity Temperature Dependence




Figure 2 shows the variation in sensitivity caused by changes in temperature. Repeatable temperature dependence at elevated temperatures allows more accurate temperature compensation.

This data is taken from a typical batch of sensors. The mean and ±95% confidence intervals are shown.

Figure 3 Zero Temperature Dependence




Figure 3 shows the variation in zero output caused by changes in temperature, expressed as ppm gas equivalent, referenced to zero at 20°C.

This data is taken from a typical batch of sensors.






Figure 4 shows sensor output for increasing concentrations of CO, up to twice the specified overgas concentration. Data shown is eight sensors taken from a typical production batch.

This stepped overgas test shows the robustness of the sensor with fast response and straight plateaus at each step.

### Apollosense Ltd

Shenzhen:

Adress: Room 712, Huaneng Building, Shennan Zhong Road, Shenzhen 518031,

Tel: (86-755) 83680810 83680820 83680830 83680860 Fax: (86-755) 83680866

Hong Kong:

Adress: Unit 1502, Hollywood Plaza, 610 Nathan Road, Mong Kok, Kln., H.K.

Tel: (852) 2737 0903 Fax: (852) 2737 0938 Email: sales@apollounion.com